

## AC/DC CURRENT CLAMP 3100 WITH BAG

**Article number: 111493**

AC/DC current clamp 3100 CAT III/1000 V. AC/DC current measurement up to 400A, voltage measurement up to 1000 V AC and 1500 V DC. Measurement of resistance ( $\geq 40 \text{ MOhm}$ ), capacitance (10 nF..100  $\mu\text{F}$ ) and frequency ( $\geq 10 \text{ MHz}$ ). Diode test and continuity test. With automatic switch-off and self-test function. Includes 2 test leads and 2 batteries. Bag included.



Attribute	Value
Display	digital
Multiple display	No
With screen backlighting	No
Measuring range selection	manuell/automatisch
Temperature measurement	No
Capacitance measurement	Yes
Frequency measurement	Yes
Continuity test	Yes
True RMS value measurement (TRMS)	No
Interface	No
Measured value memory	Yes
Measuring circuit category	CAT III
Max. Voltage Measuring circuit category	1000
Power measurement	No
Analog bar graph display	No
Current measuring range/DC	10 - 400
Current measuring range/AC	10 - 400
Type of current	AC/DC
Voltage measurement, AC	Yes
Voltage measurement, DC	Yes
Resistance measuring range	Yes
Leakage current measurement	No

CIMCO Werkzeuge GmbH & Co. KG  
Hohenhagener Straße 1 – 5  
42855 Remscheid  
Telefon +49 2191 3718-01  
info@cimco.de • cimco.de

Harmonic measurement	No
Measurement in cable with forward and return conductor	Yes
Pliers opening	35
Version as adapter for connection to multimeter	No

GTIN: 4021103107058

CIMCO Werkzeuge GmbH & Co. KG  
Hohenhagener Straße 1 – 5  
42855 Remscheid  
Telefon +49 2191 3718-01  
info@cimco.de • cimco.de